

12V/24V 20A PWM Solar Charge Controller with Dual USB

This 12V/24V 20A PWM solar charge controller efficiently charges batteries using solar panels. It features dual 5V 2A USB outputs and supports lead-acid, lithium-ion, and LiFePO4 batteries with comprehensive protection features.



Product Overview

Intelligent PWM Solar Charge Management

This 20A PWM solar charge controller is designed for efficient 12V/24V battery system management. It features a large LCD display for real-time monitoring and parameter customization, ensuring optimal charging through three-phase PWM technology. Built with safety in mind, it includes comprehensive protections against overcurrent, short circuits, and reverse polarity, alongside a memory function that retains user settings after power interruptions.

Technical Specifications

Rated Current

20 A

Rated Current

System Voltage

12V, 24V

USB Output

5V 2A (Dual USB)

Battery Compatibility

Supported Battery Types

- B01: Lead-acid battery
- B02: Lithium-ion battery
- B03: Lithium iron phosphate (LiFePO4) battery

Features & Protection

Safety Protections

Overcurrent Protection • Short Circuit Protection • Open Circuit Protection • Battery Reverse Protection • Anti-Reverse Circuit

Charging Stages

- Constant Current Mode
- Constant Voltage Mode
- Floating Charge Mode

Advanced Functions

Power-cut memory function (retains user settings)