

# 2.5kW Portable Gasoline Generator with Copper Wiring

This gasoline generator delivers a rated output of 2500 watts at 220V and 50Hz, with a peak output of 2800 watts for starting larger equipment. It features a forced air-cooled 4-stroke engine, copper wiring, and an 8" wheel kit for portability, with a long run time of up to 11 hours per tank.



## Overview

### Reliable Portable Power Solution

This 2.5kW portable gasoline generator is engineered for versatility and consistent performance in demanding environments. Powered by a robust 196cc GX200 engine, it delivers dependable AC and DC power for tools and appliances. Designed with mobility in mind, the unit features an integrated wheel kit and handle for easy transport across job sites.

## Performance Metrics

### Rated AC Output

**2500 W**  
Rated Power

**2800 W**  
Max Power

### Run Time per Tank

Load Condition	Duration
Rated Load	7 hours
1/2 Load	11 hours

## Engine Specifications

Engine Displacement	196 cc
Starting System	Recoil

## Electrical Specifications

AC Voltage	220 V
DC Output	100W 12V 8.3A

## Physical Characteristics

Fuel Tank Capacity	15 L
Dry Weight	44 kg
Dimensions (L x W x H)	650 x 465 x 470 mm

## Operational Details

Noise Level	68 dB(A)
-------------	----------

## Logistics

FCL Quantity (20'/40')

225 / 450