

## 2.7kW Gasoline Generator with Copper Wire

This gasoline generator delivers a rated output of 2.5 kW and a maximum output of 2.7 kW. It includes a 5.5 HP engine and a 12V7A battery for electric ignition.



### Overview

#### Reliable Power Solution

This 2.7kW gasoline generator is engineered for consistent performance, featuring a durable 4-stroke OHV engine and 100% copper wiring for enhanced conductivity. Designed for versatility, it provides both AC and DC power outputs, making it suitable for a wide range of industrial and commercial applications. The unit includes an electric starting system for convenience and operates with a noise level of 65 dB at 7 meters.

### Performance Metrics

#### Power Output

**2.7 kW**

Max Output

**0.75 kW**

Rated Output

**11.4 A**

Rated Current

### Technical Specifications

#### Engine Specifications

Feature	Specification
Engine Model	TE200E
Displacement	196 cc
Engine Type	Forced air-cooled, 4 stroke, OHV
Max Output	6.5 HP

#### Electrical Characteristics

- Frequency: 50 Hz
- Voltage: 220 V
- DC Output: 12V / 8.3A
- Ignition System: Non-contact transistorized ignition (T.C.I)

### Operational Features

#### Capacity & Noise

- Fuel Tank Capacity: 15 L
- Oil Capacity: 0.6 L
- Noise Level (at 7m): 65 dB

#### Starting System

Electric Start

## Logistics

### Shipping Information

- Package Dimensions: 610 x 500 x 460 mm
- Gross Weight: 57 kg
- 20' FCL Capacity: 215 pcs

## Certifications

### Compliance

CE, ISO 9001