

# 800W RMS Bluetooth Party Speaker with LED Lights

This Bluetooth party speaker delivers 800W RMS power through dual woofers and tweeters. It has USB, SD card, and AUX inputs, a customizable LED system, and a microphone input.



## Product Overview

### High-Performance Party Audio System

This powerful 800W RMS speaker system is engineered to deliver a rich, full-range audio experience, making it perfect for both indoor and outdoor events. Featuring dual woofers and integrated DJ effects, it provides versatile sound management including bass and EQ adjustments. With customizable LED lighting and karaoke-ready inputs, this speaker serves as a complete entertainment solution for professional gatherings and social events.

## Technical Specifications

### Power Output

**800 W**

Total RMS Power

**200 W**

Power per Channel

### Audio & DJ Controls

Bass Management, EQ Adjustment, Auto DJ, Manual DJ

## Connectivity

### Interface Ports

Port Type	Quantity
Microphone Input	1
Guitar Input	1
Line In (3.5mm)	1
USB Playback	1
USB Charging Port	1

### Wireless Streaming

Yes

## System Features

### Integrated Features

- Flashing LED light system
- FM Tuner
- Amber color LED display
- USB 2.1A charging output